

The EP-2000 is the most powerful controller in the EP Series. With a rock-solid warranty, and an MSRP comparable to most 1000-amp controllers, the EP-2000 is in a class by itself. Its rugged construction and unique plug-and-play design make it the only choice for high power applications.



With over twice the power capacity of the EP-1000, the EP-2000 is indeed in a class by itself. From large trucks, to marine, to hard-core racing applications, no other controller quite measures up.

The EP-2000 was designed from the ground up for severe duty applications. It's built to succeed where most other controllers fail.

And with over 2000 amps of available power, this powerhouse will never fail to perform.

Fully compatible with all brushed DC motors, including Series-Wound, Permanent Magnet, and Separately Excited motors.

BATTERY VOLTAGE: 12 - 350 VOLTS
CURRENT RANGE: 0 - 2000 AMPS
PEAK CURRENT: 3200 AMPS
THROTTLE RANGE: 0% - 100%
DUTY CYCLE: CONTINUOUS @ 1360 AMPS
CURRENT LIMITER: NONE
SPEED CONTROL: 3-WIRE POTENTIOMETER
SWITCH: +12V to turn ON
PROGRAMMABLE: NO (factory only)
ENCLOSURE: NON-METALLIC NEMA 4X
(WATERPROOF) 14 x 12 x 7 INCHES
WARRANTY: ONE YEAR, NO FAULT